## Goundwire setup for webconnex. See the last 2 pages for QR codes

10:51 • 4 webco		* ** •• • •• : **	Tap the menu icon (3 dots, top right)
	4 Add to Contacts	Ø	
1	2 ABC	3 DEF	
4	5 JKL	6	
7 PQRS	8 тиу	9 wxyz	
*	Ç	#	
		<	
11:47 <b>•</b> 4	⊾⊙• Settings	* * 11 🗊	Under Notifications, tap Incoming Calls and select Push Notifications.
Acco	unt settings Accounts		This is important because it saves battery and allows incoming calls when the phone is asleep.
Notif	cations		When done, tap Accounts
5	Incoming Calls Push Notifications		
٥	System notification	settings	
R	Push notifications to	est	
Prog	am settings		
\$	Preferences		
*	Add-ons		
4	Permissions		
	nation	<	

10:43 ● 🖻 🛦 • ← Accounts	* S 4 3	Tap + to add a new account (bottom right)
Enabled Accounts		In this screenshot I already have the account for webconnex
ECCTEC	≫ =	so I would tap that.
😋 webconnex	≥ ≥	
Disabled Accounts		
MISCorp	=	
Icon Legend		
Marks the account to be outgoing calls	e used for	
C The account will registe incoming calls from the the app is in the background	device when	
The account will register incoming calls from our handles push when the background or closed	server that	
	+	
III O	< _	
10:26 ● ■ ▲ • ← Edit SIP Account	ক্ষণ হয় ►	Give the account a Title
Title		EG. webconnex or Work
webconnex		Username: (provided by admin)
Username		Password: (provided by admin)
61294964064		Next, tap Advanced Settings
Password		
Domain		
sip54.olcs.com.au		
Advanced Settings		
III O	<	

10:39 <mark>()</mark> 🛦 🕐 🔸	* 🖘 11 🕢	Tap <b>Codec for Wi-Fi</b>
← Codecs For Wi-Fi	~	Set these Codecs
Enabled Codecs		You can drag them around with the handle that looks like =
Opus	=	Tap the back icon when done (Top left)
G.722	=	
G.711 A-law	=	
G.711 μ-law	=	
Disabled Codecs		
Codec 2	=	
G.729A	=	
GSM (RPE-LTP)	=	
Drag-and-drop items to mo between enabled and disabl and change their order.		
Packet Time III O	<	
10:39 🔶 🖻 🛦 •	* 🕾 .il 💷	Tap Codec for Mobile Data
← Codecs For Mobile Data	a 🗸	Set these Codecs
Enabled Codecs		You can drag them around with the handle that looks like =
Opus	=	Tap the back icon when done (Top left)
G.722	=	
G.711 A-law	=	
G.711 μ-law	=	
Disabled Codecs		
Codec 2	=	
G.729A	=	
GSM (RPE-LTP)	=	
Drag-and-drop items to move between enabled and disablee and change their order.		
Packet Time	<	



10:40 ● © ▲ • * * * * * * * *	₩ (B)	Swipe up to see these settings
VoiceMail Number 61211440000		Enable <b>Call Waiting</b> (so you done miss a call)
Auth User Name		Set the Transport Protocol to tls (sips)
61294964064		
Display Name		
Stuart Edge		
Outgoing calls need registration		
Call Waiting	•	
Transport Protocol		
tls (sips)		
Push Options		
DTMF mode		
Secure Calls		
III O <		
10:40 🔄 🔵 🛦 • 🔅 🕷	\$ .al 🕢	Tap DTMF Mode
← DTMF mode	~ -	This is used for responding to auto attendant menus (Dial 1
Enabled DTMF Modes	1	for this, dial 2 for that, etc.)
SIP INFO	=	You can drag them around with the handle that looks like =
Disabled DTMF Modes		Tap the back icon when done (Top left)
RFC 2833	=	
audio	=	
Drag-and-drop items to move the between enabled and disabled gro and change their order.		
Send All Enabled		
When turned on, all enabled DTMF methods are sent simultaneously. pressing a single digit results in multiple presses on the receiver si just remove the check.	lf	
III O <		

$\leftarrow$ Secure Calls $\checkmark$	Tap Secure Calls
	Note: External calls are <b>always</b> insecure.
SDES (RFC 4568)	You can enable these for incoming and outgoing
Incoming Calls	
Enabled	Tap the back icon when done (Top left)
Outgoing Calls	
Best Effort	
By default, SDES requires a secure signaling channel, such as TLS. Please note that SDES is vulnerable to man-in-the-middle attacks and largely depends on the behavior of proxies along the SIP path. There may be hops where keys are transmitted in clear text. If you wish to use SRTP over an insecure signaling channel while maintaining security, consider using ZRTP. Alternatively, you can enable "Allow SDES over Unsecure Channel" below, but this carries a risk of man-in-the-middle attacks.	
Allow SDES over Unsecure  Channel	
	Under Notifications, set expires to at least 600
III O < 0.42 • ⊙ ▲ • * ≋I @ ← Advanced Settings ✓	Under Notifications, set expires to at least 600
III O < Dx42 ● ⊙ ▲ • * ♥ J @ @ ← Advanced Settings ✓ Notifications	Under Notifications, set expires to at least 600 Tap the checkmark icon to save the setting when done
III     O     <	
III O < Dx42 ● ⊙ ▲ • * ♥ J @ @ ← Advanced Settings ✓ Notifications	Tap the checkmark icon to save the setting when done
III O < 0:42	Tap the checkmark icon to save the setting when done (Top right)
III     ○       0:42     ○ ▲ •     ★ ♥I       ★ Advanced Settings     ✓       Notifications       Use Global Setting       Account specific notification tones	Tap the checkmark icon to save the setting when done (Top right) Tap the back icon a couple of times to get back to the dial
III O < 0:42	Tap the checkmark icon to save the setting when done (Top right)
III       <	Tap the checkmark icon to save the setting when done (Top right) Tap the back icon a couple of times to get back to the dial
III O < Advanced Settings ✓ Notifications Use Global Setting Account specific notification tones Expires 600 Registration period. The server may ask to increase this value	Tap the checkmark icon to save the setting when done (Top right) Tap the back icon a couple of times to get back to the dial
III O < Advanced Settings ✓ Notifications Use Global Setting Account specific notification tones Expires 600 Registration period. The server may ask to increase this value Subscription Expires	Tap the checkmark icon to save the setting when done (Top right) Tap the back icon a couple of times to get back to the dial
III       ○         0:42       ○ ▲ •       ● ◎         ★ Advanced Settings       ✓         Notifications       ✓         Use Global Setting       ✓         Account specific notification tones       Expires         600       Registration period. The server may ask to increase this value         Subscription Expires       300         Sip subscription refresh period,	Tap the checkmark icon to save the setting when done (Top right) Tap the back icon a couple of times to get back to the dial
III O < Advanced Settings Advanced Settings Notifications Use Global Setting Account specific notification tones Expires 600 Registration period. The server may ask to increase this value Subscription Expires 300 Sip subscription refresh period, affects BLF subscriptions, MWI etc.	Tap the checkmark icon to save the setting when done (Top right) Tap the back icon a couple of times to get back to the dial
III O C Advanced Settings C Advanced Settings C Notifications Use Global Setting Account specific notification tones Expires 600 Registration period. The server may ask to increase this value Subscription Expires 300 Sip subscription refresh period, affects BLF subscriptions, MWI etc.	Tap the checkmark icon to save the setting when done (Top right) Tap the back icon a couple of times to get back to the dial

QR code for iPhone

	QR code for Android app installation.	
--	---------------------------------------	--