

Unify Phone

Unify Phone V3 for Android

OpenScape Voice OpenScape 4000

User Guide 05/2025

🕅 Mitel

Notices

The information contained in this document is believed to be accurate in all respects but is not warranted by Mitel Europe Limited. The information is subject to change without notice and should not be construed in any way as a commitment by Mitel or any of its affiliates or subsidiaries. Mitel and its affiliates and subsidiaries assume no responsibility for any errors or omissions in this document. Revisions of this document or new editions of it may be issued to incorporate such changes. No part of this document can be reproduced or transmitted in any form or by any means - electronic or mechanical - for any purpose without written permission from Mitel Networks Corporation.

Trademarks

The trademarks, service marks, logos, and graphics (collectively "Trademarks") appearing on Mitel's Internet sites or in its publications are registered and unregistered trademarks of Mitel Networks Corporation (MNC) or its subsidiaries (collectively "Mitel), Unify Software and Solutions GmbH & Co. KG or its affiliates (collectively "Unify") or others. Use of the Trademarks is prohibited without the express consent from Mitel and/or Unify. Please contact our legal department at iplegal@mitel.com for additional information. For a list of the worldwide Mitel and Unify registered trademarks, please refer to the website: http://www.mitel.com/trademarks.

© Copyright 2025, Mitel Networks Corporation

All rights reserved

Contents

1 Changes in current issue	5
2 Overview	6
2.1 Unify Phone	6
2.2 Prerequisites	
2.3 Supported Android platforms	7
3 Accessing Unify Phone	8
3.1 Getting Unify Phone	
3.2 Signing in	
3.2.1 Signing in to Unify Phone for Unify Video	8
3.2.2 Signing in to Unify Phone for OpenScape with your Unify Phone credentials	9
3.2.3 Signing in to Unify Phone for OpenScape with Single Sign On (SSO)	
3.2.4 Signing in to Unify Phone for OpenScape with a QR code	
3.3 Signing out	
3.4 Resetting your password	
4 Calls	
4.1 Making a call from the keypad	14
4.2 Making a call from the call history	14
4.3 Making a call from favorites	
4.4 Making a call from contact's profile	
4.5 Receiving a call	
4.6 Actions during a call	
4.7 Sending DTMF commands on an active call	
4.8 Placing a call on hold.	
4.9 Pushing an ongoing call to desk phone or alternative number	
4.10 Transferring a call	
4.10.1 Transferring a call with consultation.	
4.10.2 Transferring a call with consultation.	
4.12 Receiving a call during another active call.	
4.13 Swapping between two parallel calls	
4.14 Merging two parallel calls	
4.15 Call quality indicator.	
4.15.1 Call metrics	
4.16 Pulling an ongoing call from another device	24
4.17 Working as an agent in classic hunt/ACD groups	
4.18 Name resolution of phone numbers	26
5 Call history	
5.1 Filtering the call history	
5.2 Deleting the call history	
5.3 Deleting an entry from the call history	
6 Voicemail	30
6.1 Listening to voice messages	
7 Presence	
7.1 Presence in Unify Phone for Unify Video7.2 Presence in Unify Phone for OpenScape	
7.3 Setting your presence status	
7.4 Setting a profile picture	

7.5 Removing the profile picture	
 8 Contact directories	35 36
9 Favorites	
9.1 Marking a contact's phone number as a favorite	
9.2 Reordering favorites	
9.3 Removing a favorite	
10 Settings	40
10.1 Enabling call forwarding	
10.2 Disabling call forwarding	
10.3 Setting an alternative number	
10.4 Changing the ring time before a call is routed to alternative number	
10.5 Activating your voicemail	
10.6 Configuring incoming call routing	
10.7 Configuring busy settings	
10.8 Selecting a theme.	
10.9 Connecting to your Microsoft Exchange account	
10.11 Connecting to your Google account	
10.12 Making yourself available for hunt/ ACD group calls	
10.12.1 Making yourself available for hunt group calls (OpenScape Voice)	
10.12.2 Making yourself available for ACD group calls (OpenScape 4000)	
10.12.3 Making yourself available for classic group calls (OpenScape 4000)	
10.13 Changing your password	
10.14 Changing the Unify Phone ringtone for incoming calls	
10.15 Viewing your account's activity	
11 Service and support	54
11.1 Accessing user documentation	
11.2 Reporting an issue	54
11.3 Viewing the terms and conditions	
11.4 Performing a required update of the Unify Phone app	
11.5 Granting additional app permissions when Unify Phone runs on a Xiaomi device	55
12 Appendix	
12.1 Switching your Chromebook to Beta channel	57

1 Changes in current issue

Impacted chapters	Change description
Calls on page 13	Updated chapter about emergency calls.
Signing in to Unify Phone for OpenScape with a QR code on page 10	New chapter about signing in with a QR code.
Supported Android platforms on page 7	Updated chapter about the supported Android platforms.

2 Overview

This guide describes how to make use of the Unify Phone mobile app on Android when working with an OpenScape Voice or OpenScape 4000 communication system.

The document contains general descriptions of the technical options, which may not always be available in individual cases.

If a particular function on Unify Phone is not available to you as described, this may be due to one of the following reasons:

- The function is not configured for you. Please contact your administrator.
- Your communication system does not feature this function. Please contact your sales partner for information on how to upgrade.

2.1 Unify Phone

Unify Phone is a cloud-based telephony connector that works with Unify OpenScape Business. It enables you to make and receive calls using your business phone number through the Unify Phone app, providing a unified and flexible communication experience across devices.

Unify Phone comes in two different flavors:

- Unify Phone for Unify Video: it is used in conjunction with Unify Video allowing Unify Video users to communicate with others via phone calls.
- **Unify Phone for OpenScape**: it is used as a stand-alone OpenScape communication system telephony client.

With Unify Phone you can easily:

- Make call
- Answer, decline or drop a call
- Send DTMF commands in a call
- Hold and retrieve
- Transfer call
- Pull call from other Unify Phone clients or desk phone
- Push call to desk phone
- Make or answer a second call
- Swap calls (alternate)
- Merge two calls into a conference
- · Call forwarding
- Alternative number (One Number Service)
- Call routing
- Voicemail
- · Add phone numbers to favorites
- View contact profile information.

Unify Phone also allows you to communicate with other users in your tenant via text and voice messages. This requires your administrator to enable the chat feature for your tenant.

2.2 Prerequisites

Prerequisites for Unify Phone for Unify Video

- You have a Unify Video account.
- You are a subscriber of one of the following communication systems:
 - OpenScape Voice V10R2.14.0 (with all the available hotfixes installed) or later
 - OpenScape 4000 V10R1 (with all the available hotfixes installed) or later
- Your communication system has been set up to integrate with Unify Video via Unify Phone.
- The necessary licenses have been assigned to you on both Unify Video and your communication system.
- Your Unify Video administrator has enabled cross-launch for you, so you are able to launch:
 - Unify Phone from Unify Video and
 - Unify Video from Unify Phone.

The Unify Video app and the Unify Phone app are tightly integrated.

• You have both the Unify Video app and the Unify Phone app open on your mobile and you have signed in to both of them, so you are able to make and receive phone calls in Unify Video.

Prerequisites for Unify Phone for OpenScape

- You are a subscriber of one of the following communication systems:
 - OpenScape Voice V10R2.14.0 (with all the available hotfixes installed) or later
 - OpenScape 4000 V10R1.34 (with all the available hotfixes installed) or later and the privates for Assistant or Manager

Classic hunt groups are supported when the OpenScape 4000 communication system is running at least on version 11.

- Your communication system has been set up to connect to Unify Phone.
- You are a Unify Phone user.
- The necessary licenses have been assigned to you on your communication system.

2.3 Supported Android platforms

The supported Android platforms for Unify Phone are:

- Phones and tablets running the Android operating system version 10 or later, up to version 14.
- Chromebooks running the Android operating system version 11.

NOTICE:

Android 11 is currently rolling out in the Beta channel of the Chrome OS. You need to switch to the Beta channel for your Chromebook to receive the update. For instructions, please refer to Switching your Chromebook to Beta channel on page 57.

3 Accessing Unify Phone

3.1 Getting Unify Phone

Step by Step

1) On your Android device, do one of the following:

- Type https://phoneapp.unify.com in your device's web browser, then tap Get it on Google Play.
- Tap the following link to be redirected to the Unify Phone page in Google Play.
 - https://play.google.com/store/apps/details?id=com.unify.ngtc
- Launch the Play Store app, search for Unify Phone, then select the Unify Phone app from the search results.
- 2) Tap Install.
- 3) Tap Accept.
- 4) When the installation completes, tap **Open** to launch the app.

3.2 Signing in

This section describes how to sign in to:

- Unify Phone for Unify Video
- Unify Phone for OpenScape, with your Unify Phone credentials
- Unify Phone for OpenScape, with Single Sign On (SSO)
- · Unify Phone for OpenScape, with QR code

3.2.1 Signing in to Unify Phone for Unify Video

You can sign in to Unify Phone for Unify Video using your Unify Video account credentials.

Step by Step

- 1) Open Unify Phone with any of the following ways:
 - ^{a)} Go to the Unify Video app and tap & at the bottom menu.



b) Open the Unify Phone app from your device.

The Unify Phone app opens prompting you to sign in.

Unify Phone
SIGN IN

- 2) Tap Sign In.
- Enter the email address associated with your Unify Video account and tap Next.
- 4) Enter the email address or phone number associated with your Unify Video account and tap **Next**.
- 5) Enter the password and tap Sign In.
- Tap Authorize to allow both Unify Phone app and Unify Video to access your account information.
- 7) Tap Allow to grant the Unify Phone app permission to make and manage phone calls.
- 8) Tap Allow to grant the Unify Phone app permission to record audio.

3.2.2 Signing in to Unify Phone for OpenScape with your Unify Phone credentials

When Unify Phone is used as a stand-alone telephony client, you can sign in to the app using your Unify Phone account credentials.

Step by Step

 Open the Unify Phone app from your device. The Unify Phone app opens prompting you to sign in.

- 2) Tap Sign In.
- 3) Enter the email address associated with your account and tap Next.
- 4) Enter the password associated with your account.

If you can not remember your password, tap **Forgot password?**, enter the email address associated with your account, and then tap **Reset**. An email with a link to reset your password will be sent to you. For more information, see Resetting your password on page 11.

If you receive a message stating that your password has expired, follow the instructions sent to you via email to set a new password.

NOTICE: By default, your password is set to expire automatically every 90 days. You will receive an email reminder 7 days prior to your password expiration date. Remember to check your junk or spam folder if you can't find the email in your inbox.

3.2.3 Signing in to Unify Phone for OpenScape with Single Sign On (SSO)

Single Sign On Authentication (SSO) allows you to sign in to multiple applications using a single set of credentials. If your administrator has activated SSO for your Unify Phone for OpenScape tenant, you can use your organizational account to sign in to the Unify Phone app.

NOTICE: This option is only available for Unify Phone for OpenScape.

Step by Step

- Open the Unify Phone app from your device. The Unify Phone app opens prompting you to sign in.
- 2) Tap Sign In.
- Enter the email address associated with your account and tap Next.
- 4) You are redirected to the SSO provider's sign-in page. Sign in with organizational account credentials. After successful authentication, you are redirected back to the Unify Phone app.

3.2.4 Signing in to Unify Phone for OpenScape with a QR code

You can sign in to the Unify Phone app by scanning a QR code with your mobile device. You can find the QR code in the account settings of your Unify Phone for Web or PWA client.

Prerequisites

 Your Unify Phone web client or PWA is currently open on a desktop computer, displaying the sing-in QR code under Settings > Account.

or

⁵⁾ Tap Sign In.

• You have saved the sing-in QR code in the gallery app on your mobile device.

To sign in to Unify Phone, follow the steps below and scan the QR code from within the app:

Step by Step

- 1) Open the Unify Phone app from your device. The Unify Phone app opens prompting you to sign in.
- 2) Tap 🖭 next to the Sign in button.

Your camera is activated.

- **3)** If prompted, click **Allow** to allow the Unify Phone app to use your device camera.
- 4) Scan the QR code on your computer screen or tap the Gallery icon and select the QR image.

You are redirected to the sign in page where your email address is already filled in.

- 5) Tap Next.
- 6) Enter your the password associated with your account.

If you can not remember your password, tap **Forgot password?**, enter the email address associated with your account, and then tap **Reset**. An email with a link to reset your password will be sent to you. For more information, see Resetting your password on page 11.

7) Tap Sign in.

You can alternatively scan the QR code by manually opening your device's camera app, then scanning the QR code (or tapping the Gallery icon and selecting the QR code). This will redirect you to the sign-in page, where your username is already populated. Tap **Next**, enter your password, then tap **Sign in** to sign in to Unify Phone.

3.3 Signing out

To sign out at any time:

Procedure

• Tap ≡ in the top left of the app, then select **Sign out** from the navigation drawer.

3.4 Resetting your password

You can reset your password for Unify Phone for OpenScape if you forget it.

NOTICE: If you sign in to Unify Phone for OpenScape through Single Sign On (SSO) you cannot reset your password by

following the steps outlined below; you must reset your password in the third-party service that provides the SSO.

Step by Step

- 1) On the Unify Phone for OpenScape sign in screen, tap Forgot password?.
- 2) Enter the email address associated with your account then tap **Reset**. An email with a link to reset your password will be sent to you.
- Go to your email inbox and open the email with the subject Unify Phone for OpenScape: Reset password.

NOTICE: Remember to check your junk or spam folder if you can't find the email in your inbox.

- 4) Tap **Reset password** in the email to open the link for resetting your password.
- 5) Enter your new password in the **New password** field, then enter it again in the **Confirm new password** field.

The password must conform to the password requirements displayed.

As you type in, a visual strength indicator shows how secure your password is.

For security reasons, you cannot reuse a few passwords that you have previously set on your account. If the new password matches a recent password from the password history cache, an error message is displayed prompting you to choose a different password.

6) Tap Submit.

Your password is reset.

NOTICE: Your password is set to expire automatically every 90 days. You will receive an email reminder 7 days prior to your password expiration date. We recommend changing your password before it expires to avoid losing access to your account.

4 Calls

With Unify Phone you can easily make and receive phone calls.

As an **OpenScape Voice subscriber**, you can make or receive up to two calls at a time on a Unify Phone client (web or mobile). Only one call can be active at a time on a client. Others can be either incoming calls or calls on hold. If you are already handling two calls on a client, any additional incoming calls be sent to other destinations, such as your desk phone. You can be in more than two phone calls simultaneously on Unify Phone, but not all on the same client. For example, you can be on two phone calls on the web app, and on another one on the mobile app.

As an **OpenScape 4000 subscriber**, you can make or receive up to two calls in total on Unify Phone. Only one call can be active at a time on a client. Others can be either incoming calls or calls on hold. If you are already handling two calls on Unify Phone (either both on the same client or on different clients), any additional incoming calls will be sent to other destinations, such as your desk phone.

The first time you make a call or listen to your voicemail using Unify Phone, you will be required to read and accept the Emergency calls disclaimer. The disclaimer explains that you should use a mobile phone call (GSM) or a landline phone to make emergency calls instead of Unify Phone. A mobile or landline phone will provide a more accurate location to help emergency services find you. Additionally, emergency calls made through Unify Phone may be routed to the incorrect response center. Once you accept the disclaimer, it will not appear again.

4.1 Making a call from the keypad



Step by Step

- 1) Open Unify Phone.
- 2) If a desk phone has been assigned to you on your OpenScape system or you have set an alternative number in <u>Settings</u> (e.g. mobile), you can select the device to make the call from as follows:
 - a) Tap Call
 next to the call button and select your preferred option between Unify Phone (default), Desk phone or Alternative number.
 The selected device will be remembered as the preferred device for calls initiated through the specific Unify Phone client.
- 3) Use the on-screen keypad to enter a number and tap the call button.

4.2 Making a call from the call history

Step by Step

- 1) Open Unify Phone.
- 2) Tap () History at the bottom of the app.

- Locate the call history entry you want to call and do one of the following actions:
 - Tap the entry you want to call.

The call is made using the device you last selected in the Keypad area or after performing a long tap on a contact's name or number in the call history, the favorites list or in the contact search results.

• Long tap the entry you want to call and select the preferred calling device from the available options.

The call is made using the device you have selected. The selected device will be remembered as the preferred device for calls initiated through the specific Unify Phone client.

4.3 Making a call from favorites

Step by Step

- 1) Open Unify Phone.
- ²⁾ Tap Favorites at the bottom of the app.
- 3) Do one of the following:
 - Tap the favorite you want to call.

The call is made using the device you last selected in the Keypad area or after performing a long tap on a contact's name or number in the call history, the favorites list or in the contact search results.

• Long tap the favorite you want to call and select the preferred calling device from the available options.

The call is made using the device you have selected. The selected device will be remembered as the preferred device for calls initiated through the specific Unify Phone client.

4.4 Making a call from contact's profile

Step by Step

- 1) Go to the profile of the contact you want to call in one of the following two ways:
 - ^{*} Tap ^{****} **Keypad** at the bottom of the app, tap ^Q at the top right, search for the contact's name or phone number, then tap on the contact's profile picture in the search results.
 - Tap \bigcirc **History** at the bottom of the app, tap on the profile picture of the contact in the call history.

- 2) Do one of the following:
 - Tap the phone number you want to call.

The call is made using the device you last selected in the Keypad area or after performing a long tap on a contact's name or number in the call history, the favorites list or in the contact search results.

• Long tap the phone number you want to call and select the preferred calling device from the available options.

The call is made using the device you have selected. The selected device will be remembered as the preferred device for calls initiated through the specific Unify Phone client.

4.5 Receiving a call

You can easily receive phone calls through Unify Phone. When a call comes in, you will see the incoming call alert on the display of your mobile phone and you will get an audio notification.

You can select to answer or decline the call or send the call to voicemail (if voicemail is enabled for you).

If you have a desk phone or you have set an alternative number (e.g. mobile) via the web app, you will also get the option to answer the call from the respective device.



Procedure

To answer the call, swipe up the answer icon S.

- To decline the call, swipe up the decline icon
- To send the call to voicemail, select **Decline > Voicemail**.
- To answer the call from your desk phone, select **Answer > Desk phone**.
 - To answer the call from your alternative phone, select Answer > Alternative number.

NOTICE:

The name of the caller is only displayed when it can be resolved (e.g. from contacts).

NOTICE:

The **Answer** drop-menu menu is visible if a desk phone has been assigned to you on your OpenScape system or if you have set an alternative number.

Only options that are available to you are listed in the **Answer** drop-down.

4.6 Actions during a call

While in a call, you can see the name or number of the person you are on a call with on the call screen, the duration of the call, the call metrics and a set of call controls.



The following table summarizes the call controls and their functions.

Calls

lcon	Action	Description
X	Mute	Mute or unmute your microphone
****	Keypad	Open a keypad to enter DTMF (dual tone multi-frequency) digits
<)» (*	Speaker	Enable or disable your loudspeaker
	Hold	Place the call on hold or retrieve the call ¹
% ⁺	New call	Make a new separate call ¹
000	More	 Display more call control options: □+ <i>Transfer</i>: Transfer the call to another number ↑ <i>Merge</i>: Merge two parallel calls to bring them into a conference² ♥ <i>Swap</i>: Swap two separate calls²
0	End call	End the current call
	Push to desk phone	Push the current call to desk phone ³
B	Push call to alternative number	Push the current call to alternative number ⁵
C	Push call	 Display the following options to push the call to⁶: Desk phone: Push the call to desk phone C Alternative number. Push the call to alternative number
St.	Pull	Pull a remote call ⁴

4.7 Sending DTMF commands on an active call

During an active call, you can send Dual-Tone Multi-Frequency (DTMF) commands.

Step by Step

- 1) Tap **## Keypad** on the call controls.
- 2) Use the on-screen keypad to enter DTMF commands.

4.8 Placing a call on hold

While on a call, you can place the call on hold so that you can perform another task like making or answering another call.

Procedure

To place a call on hold, tap II Hold on the call controls.

The other party will be placed on hold until you retrieve or transfer the call.

• To return to the call, tap || Hold again on the call controls.

4.9 Pushing an ongoing call to desk phone or alternative number

You can push an active call from the Unify Phone app to your desk phone or alternative number.

Prerequisites

- A desk phone has been assigned to you on your OpenScape system or you have set an alternative number in <u>Settings</u> on page 40 (e.g. mobile).
- You are on an ongoing call on the Unify Phone app.

- ² Available when you are on two separate calls
- ³ Available when a desk phone has been assigned to you on your OpenScape system
- ⁴ Available when you are on an ongoing call into a remote Unify Phone client or desk phone and you haven't reached the maximum call limit on your mobile app
- ⁵ Available in full screen call view when you have set an alternative number in Settings
- ⁶ Available in mini call view when a desk phone has been assigned to you on your OpenScape system or you have set an alternative number in Settings. Only options that are available to you are displayed

¹ Available when you are on a single call

Procedure

- If the call is shown in full screen:
 - Tap 🕒 on the call controls to push the call to desk phone.
 - or

• Tap ^(e) on the call controls to push the call to alternative number. Only one of these buttons is visible on the call controls at a time.

If the desired button is not displayed, tap the down arrow \checkmark on the call controls area and select the device you want to push the call to from the pop-up menu. The respective button will then appear on the call controls and be available for use.

The down arrow \checkmark is only visible, if a desk phone has been assigned to you on your OpenScape system and you have set an alternative number in Settings.

4.10 Transferring a call

You can transfer an active call to another person with or without consultation.

4.10.1 Transferring a call without consultation (blind transfer)

While on an active call:

Step by Step

- 1) Tap *** More.
- 2) Select [] > Transfer from the drop-down menu.
- 3) Enter the name or number you want to transfer the call to.
- **4)** When you finish typing, tap ^[]→ **Transfer**.

The call is transferred and you are disconnected from the call.

4.10.2 Transferring a call with consultation

You can speak with the person you want to transfer the call to before actually transferring the call.

While on an active call:

Step by Step

- 1) Tap St New call on the call controls.
- 2) Enter the number you want to transfer the call to.
- When you finish typing, tap ^{S⁺}.

- **4)** The first call is put automatically on hold so you can talk privately with the third party.
- 5) To transfer the call:
 - a) Tap •••• More on the call controls.
 - b) Select ^[]→ **Transfer** from the drop-down menu.

The call is transferred and you are disconnected.

4.11 Making a second parallel call

You can make a new call, while already in a call.

Step by Step

- 1) Tap St New call on the call controls.
- 2) Enter the number you want to call.
- **3)** When you finish typing, tap .

The first call is put automatically on hold and the second one is initiated.

4.12 Receiving a call during another active call

When a call comes in while you are engaged in an active call, you will see the incoming call alert on your display and you will get an audio notification.

You can select to answer the call or send the call to voicemail (if voicemail is enabled for you).

If you have set an alternative phone (e.g. mobile) via the web app, you will also get the option to answer the call from the respective device.

Calls Swapping between two parallel calls



Procedure

- To answer the call, swipe up the answer icon S.
- To decline the call and send it to voicemail, swipe up the voicemail icon ¹⁰⁰
- To answer the call from your desk phone, select **Answer > Desk phone**.
- To answer the call from your alternative phone, select Answer > Alternative number.

NOTICE:

The **Answer** drop-menu menu is visible if a desk phone has been assigned to you on your OpenScape system or if you have set an alternative number.

Only options that are available to you are listed in the **Answer** drop-down.

When you answer the second call, the first call is put automatically on hold.

4.13 Swapping between two parallel calls

You can swap between an active call and a call on hold. When you do this, the currently active call is placed on hold and the call on hold becomes the active call.

To swap between two parallel calls:

Procedure

- If the call on hold is shown in full screen, tap ••• **More** on the call controls and select ^① **Swap** from the drop-down menu.
- If the call on hold is shown in mini view, tap \mathfrak{N} Swap in the call controls.

4.14 Merging two parallel calls

When you are on two calls at the same time, you can merge them into a conference:

Step by Step

1) Tap *** More on the call controls.

2) Select \uparrow Merge from the drop-down menu.

The calls are merged into one under the title **Merged call** and you can see the names or numbers of the conference participants on the call screen.

4.15 Call quality indicator

The call quality indicator $\boldsymbol{.}\boldsymbol{I}\boldsymbol{I}$ shows the quality of the connection during an active call.

The call quality indicators are described in the following table:

Call quality indicator	Call quality	
Three bars	High	All values are within the expected range.
Two bars	Average	Some values are below the expected range. Sporadic audio issues may happen.
One bar	Low	Several values are below the expected range or packet loss is high. Audio may break during the call.
No bars	Poor	Most indicators are below the expected range or packet loss is very high. Audio is likely to be unusable.

When the call quality is low (one bar) or poor (no bars), you can do the following actions:

If you are using a WiFi connection, move to an area with better network connection, or switch to another network.

If the problem persists, contact your system administrator to troubleshoot the network. Clicking on the bars to show detailed call metrics may help diagnosing the issue.

• If you are using a data (cellular) connection, move to an area with better cellular reception.

4.15.1 Call metrics

While on an active call, you can check the audio quality of the call using **Call Metrics**.

Call metrics are available after the call is established and for as long as the call is not on hold.

To view the call metrics of an audio call, tap **I** Call Metrics at the top right of the call screen. The icon appears as loading for the first few seconds of the call, then a pop-up window with the call metrics appears.

The following call metrics are collected in real time:

- Jitter is measured in milliseconds as the variation between packet delays.
- **Send packets lost** is calculated as the percentage of packets that don't make it to the destination party in the call.
- **Receive packets lost** is calculated as the percentage of packets that don't make it from the other party in the call.
- Round-trip time is measured in milliseconds as the amount of time it takes for a packet to be sent and for the acknowledgment of the packet to be received.

Unify Phone collects call metrics every two seconds.

Metrics exceeding their threshold are displayed in red.

The call quality indicator **I** shows the quality of the connection using bars. For more information about call quality indicator, see Call quality indicator on page 23.

4.16 Pulling an ongoing call from another device

You can move an active call from the device where you answered it to another preferred device by pulling it onto the new device. For example, if you are on a call through your web app or desk phone, you can pull the call onto your mobile app to seamlessly continue the conversation.

The text Remote call is displayed next to the status of the call on all inactive devices on which you signed in.

Prerequisites

• You are on an ongoing call into a remote Unify Phone client or desk phone.

To pull the call on the mobile app:

Step by Step

- 1) Open the Unify Phone mobile app.
- 2) Tap **V** Pull on the call controls.

4.17 Working as an agent in classic hunt/ACD groups

NOTICE:

In case of OpenScape Voice, the agents are members of hunt groups.

In case of OpenScape 4000, the agents are members of ACD (Automatic Call Distribution) groups or classic hunt groups.

Hunt/ ACD groups allow a group of people to answer incoming calls to a single phone number. Hunt/ ACD group calls are distributed to members of the group in an ordered manner according to the rules specified by the administrator of the communication system.

If you are a member of a hunt/ ACD group, you will be able to receive calls to the hunt/ ACD group number. You will still be able to receive direct calls to your own work number, when it is different from the hunt/ ACD group number.

As an OpenScape Voice subscriber, receiving hunt group calls requires that:

- You are a member of at least one hunt group.
- Your agent status is set to available for all hunt groups or for a specific one.

As an **OpenScape 4000 subscriber**, receiving ACD or classic hunt group calls requires that:

 You are a member of either an ACD group or a member of one or more classic hunt groups.

NOTICE: As a Unify Phone user, you cannot be part of both an ACD group and one or more classic hunt groups at the same time.

• Your agent status is set to available.

When a hunt/ ACD group call comes in on your device, the incoming call screen shows up on your display and you can hear a ringtone.

When a hunt group call comes in for an OpenScape Voice subscriber, the incoming call screen shows the following information:

- The number or name of the calling party
- The pilot number/ display name of the hunt group that the call has been forwarded from.

NOTICE: This allows you to difference between a hunt group call and a regular incoming call.

When a hunt/ ACD group call comes in for an OpenScape 4000 subscriber, the incoming call screen shows the number or name of the calling party.

You can choose to answer or decline a hunt/ ACD group call that comes in on your device.

If you do not answer a hunt group call within a set time, the call follows the rules of the specific hunt group configuration.

4.18 Name resolution of phone numbers

Unify Phone searches for users or contacts by their phone number and attempts to add naming information to them. This action is referred here as name resolution.

A phone number can be resolved to a name only if it is associated with only one user. It is required that your communication system has been configured to send Fully Qualified Numbers to Unify Phone.

Any name resolution attempt is done first on Unify Phone users. If the number cannot be resolved, your Unify Phone app will attempt to resolve the name through external services. If 2 (or more) external services are connected and they both resolve to a name, there is no specific priority which name will be used.

Name resolution of Unify Phone users

When resolving a phone number displayed on a Unify Phone client, Unify Phone searches the phone numbers of all Unify Phone users that belong to the same tenant.

Name resolution of non-Unify Phone users

By default, Unify Phone can only resolve phone numbers that belong to Unify Phone users. If you need to resolve names of non-Unify Phone users, you must integrate with external services. The following external services are supported for name resolution:

Microsoft Exchange	Name resolution in Microsoft Exchange is only possible for private contacts. After connecting to Microsoft Exchange (Online or on-premises) for the first time, it might take a while for the name resolution to work.
Google Contacts	Unify Phone can resolve your private Google Contacts. After connecting to your Google account for the first time, it might take a while for the name resolution to work.
Local contact lists in mobile clients	An external service available for Unify Phone mobile clients is their own local contact list. This is automatically enabled once the user gives the Unify Phone app permission to access the contact list.

Persistence of resolved phone numbers in the call history

If call history entries items are resolved to Unify Phone users, this information is persistent across clients and client sessions (sign ins / sign outs).

If a call history item could not be resolved to a Unify Phone user, the clients will attempt to resolve it through the external services. However, this information is not persistent. This means that different clients may display the same call history entries differently, depending on which external service was used to resolve them.

5 Call history

Call history is the list of all your incoming and outgoing calls. You can use it to call your contacts again or to respond to a missed call.

To view the call history, tap **History** \odot at the bottom of the Unify Phone app.

Identification of calls

The entries in the call history are identified as follows:

Symbol	Description
بر	Incoming call, answered
ن	Incoming call, missed
マ	Outgoing call

New calls in the call history are indicated by a vertical red line to the left of the call entry.

Call details

Further information about calls is listed in the call history:

- Avatar of the caller/ callee
- Phone number of the caller/ callee
- Name of the caller/ callee

The name is only displayed when it can be resolved (e.g. from contacts)

- Call type
- Date and time of the call
- Call duration (only for the answered calls)

Currently, if you are a subscriber of OpenScape 4000 and you are signed out of all Unify Phone clients, any incoming or outgoing call on your work number will not appear on the Unify Phone call history.

5.1 Filtering the call history

If you want to filter the call history entries, follow the steps below:

Step by Step

- 1) Tap ⁽ History at the bottom of the app.
- 2) Tap : in the top-right corner of the app.
- 3) Tap Filter and select:
 - All to view all your incoming and outgoing calls.
 - Missed to view only calls you didn't answer.

5.2 Deleting the call history

If you want to delete your full call history, follow the steps below:

Step by Step

- 1) Tap ⁽¹⁾ History at the bottom of the app.
- 2) Tap : in the top-right corner of the app.
- 3) Select Delete all.
- 4) Tap Yes to confirm that you want to delete the call history.

5.3 Deleting an entry from the call history

If you want to delete a call entry from the call history, follow the steps below:

Step by Step

- **1)** Tap ^(C) **History** at the bottom of the app.
- 2) Tap and hold the call entry that you want to delete.
- 3) Select **Delete** from the drop-down menu.
- 4) Tap Yes to confirm that you want to delete the call entry.

6 Voicemail

You can access voicemail messages via Unify Phone.

6.1 Listening to voice messages

When voicemail is enabled for you on your OpenScape system, the voicemail icon ΩO appears at the top of your Unify Phone app. The icon appears with a red dot when you receive a new voice message (currently only available with OpenScape Voice).

To listen to your voice messages:

Step by Step

- 1) Tap the voicemail icon at the top of the app to call your voicemail box.
- 2) If prompted, enter the number of the voicemail box.
- 3) Listen to messages received.
- 4) End the call by clicking \bigcirc .

7 Presence

Your presence status lets people know if you are available for communication or not.

You can also set a profile picture to be identified easily by other users.

7.1 Presence in Unify Phone for Unify Video

The presence or availability statuses in Unify Phone for Unify Video are described in the following table:

Presence / Availability status	Description	How this status gets set
Available	You are online and available to contact.	It is set automatically based on your activity or you can set your status to Available anytime you want.
On a call	You are online and on a call (either phone call or Unify Video call) or in a Unify Video meeting.	It is set automatically when you are on a phone call or in a meeting.
Do not disturb	You do not want to be disrupted. Any incoming calls will be silent.	You can set your status to Do not disturb anytime you want.
Offline	You are offline or inactive (for 15 minutes or more), or logged out of the app.	It is set automatically based on your activity.
Invisible	You want to appear as if you were offline.	You can set your status to Invisible anytime you want.

Your present status in Unify Phone is synchronized with your presence status in Unify Video and OpenScape communication system. This means, for example, that when you are on a call on your desk phone or in Unify Phone or when you join a meeting in Unify Video, your presence status will change to $On \ a \ call$ (Busy) on all clients and devices: Unify Phone, Unify Video and desk phone.

7.2 Presence in Unify Phone for OpenScape

The presence or availability statuses in Unify Phone for OpenScape are described in the following table:

Presence / Availability status	Description	How this status gets set
Available	You are online and available to contact.	It is set automatically based on your activity or you can set your status to Available anytime you want.

Presence

Setting your presence status

Presence / Availability status	Description	How this status gets set
Busy / On a call	You are online and on a call or you are busy and do not want to be interrupted.	It is set automatically when you are on a phone call.
		You can also set your presence to this anytime you want. If you manually set it to Busy , it will stay that way until you change it again.
Do not disturb	You do not want to be disrupted. Any incoming calls will be silent.	You can set your status to Do not disturb anytime you want.
Away	You are away or you want it to appear to others that you are currently away.	It is set automatically when there is no interaction with Unify Phone for a specified period of time and there is no call in progress.
		On a mobile device, your presence status is set automatically to Away when push notifications cannot be delivered to your Unify Phone app.
		You can also set your presence to this anytime you want. If you manually set it to Away , it will stay that way until you change it again or until you are logged out of the app.
Offline	You are offline or logged out of the app.	It is automatically set when you are not logged in on any of your devices.
Appear offline	You want it to appear to others that you are currently offline.	You can set your presence to this anytime you want. If you manually set it to Appear offline , it will stay that way until you change it again.

7.3 Setting your presence status

You can see your presence status in the left-side navigation drawer, on the bottom-right corner of your avatar image.



To set your presence status:

Step by Step

1) Tap \equiv in the top left of the app, then tap on your avatar image.

- 2) Select one of the presence statuses from the list of options.
 - The following presence statuses are available on Unify Phone for Unify Video:
 - Available
 - Do not disturb
 - Invisible

NOTICE: If you are on a call, the available options are On a call, Do not disturb, and Invisible.

- The following presence statuses are available on Unify Phone for OpenScape:
 - Available
 - Busy
 - Do not disturb
 - Away
 - Appear offline

NOTICE: If you do not see your presence status or the presence status of others, this would mean that your tenant has been configured to hide presence statuses.

7.4 Setting a profile picture

You can set a profile picture on your account to let other users recognize you easier.

Your profile picture is shown in the left-side navigation drawer. By default, before setting a profile picture, your initials are displayed in the avatar space.

Other user can view your profile picture during active calls or when searching for your name or number.

You can set your profile picture in one of the following ways:

- Upload a picture from your device
- Take a picture using your device camera

Step by Step

- 1) Tap \equiv in the top left of the app, then tap on your avatar image.
- 2) Tap Change picture.

- **3)** A menu is displayed at the bottom of the app and you can do one of the following:
 - a) Tap Take picture to take a picture with your device's camera.

The default camera app on your device opens allowing you to take a picture.

After taking the picture, it is displayed in preview mode and you have the following options:

- Retake the picture.
- Use the picture as your profile picture.
- Withdraw the picture and return to the Unify Phone app.
- b) Tap Upload picture to select a picture from your device's gallery.

The image gallery on your device opens and you can select the picture you want to upload.

- Once you have taken or selected a picture, you can adjust it by cropping or rotating it.
- **5)** When you are ready to set your profile picture, tap \checkmark .

Your profile picture is updated.

7.5 Removing the profile picture

You can remove the profile picture you have previously set and restore the default picture with your initials.

Step by Step

- 1) Tap \equiv in the top left of the app, then tap on your avatar image.
- 2) Tap Change picture.
- 3) On the menu displayed at the bottom of the app, tap **Remove picture**.

Your profile picture is updated to the default one with your initials.

It is not possible to reuse previous profile pictures. You need to upload or take a new image when you want to set your profile picture again.

8 Contact directories

Unify Phone brings together contacts from directories it has access to, making it easier to use all your contacts in one place.

Unify Phone supports the following contacts directories:

- Internal directory
 - Contains Unify Phone users that belong to the same tenant.
- Exchange contacts directory

Contains private and global contacts from your Microsoft Exchange accounts (Online or on-premises), as well as in your organization's users directory.

The Exchange contacts directory can be used once you connect to your company's Microsoft Exchange accounts.

For more information, see:

- Connecting to your Microsoft Exchange account on page 44
- Connecting to your Microsoft Exchange on-premises account on page 45
- Google contacts directory

Contains contacts from your Google account.

The Google Contacts directory can be used once you connect to your Google account.

For more information, see Connecting to your Google account on page 46.

Local contact directory on your mobile phone

Contains local contacts that are stored on your mobile device.

The Local contact directory on your mobile device can be used once you give the Unify Phone app permission to access the contact list.

To easily find contacts, you can search by their name or phone number. Unify Phone searches in all contact directories it has access to. For more information, see Searching for a contact on page 35.

You can tap on a contact's avatar at any time to open contact's profile page. From the profile page, you can easily:

- View contact information (avatar, name, phone number, email address).
- Mark contact's phone number as a favorite.

For more information, see Marking a contact's phone number as a favorite on page 38.

Make a call.

For more information, see Making a call from contact's profile on page 15.

8.1 Searching for a contact

You can search for a contact by name or phone number.

As you type in the search box, Unify Phone will simultaneously search in all contact directories it has access to.

If you are connected to your company's Microsoft Exchange account (Online or on-premises) or Google account and you are searching for a contact by name, Unify Phone will search in your private and global Exchange contacts.

If you are connected to your company's Microsoft Exchange account (Online or on-premises) or Google account and you are searching for a contact by phone number, Unify Phone will search in your private Exchange contacts.

Step by Step

- 1) Open Unify Phone.
- 2) In the top-right of the screen, tap Q.
 - You are navigated to the search screen.
- **3)** In the input field, type the name or number of the contact you are searching for.

The search results display the list of contacts that matches your search (if any).

You can recognize the Exchange contacts by the Microsoft Exchange icon displayed at the top right corner of their avatar:

- If or contacts in your Microsoft Exchange Online account, as well as in your organization's users directory.
- I for contacts in your Microsoft Exchange on-premises account.
- ' 🍐 , for contacts in your Google account.

Next steps

To make a call from search results, tap the desired entry and select the preferred calling device from the available options.

The call is made using the device you have selected. The selected device will be remembered as the preferred device for calls initiated through the specific Unify Phone client.

8.2 Contact profile

A contact profile stores personal information such as profile picture, name, phone number and email address.

Each contact has a profile that allows you to access all their available information and perform quick actions such as calling the contact or marking their phone number as a favorite. You can view a contact's profile by tapping on their profile picture.

8.2.1 Viewing a contact's profile

You can view a contact profile page in one of the following ways:
Procedure

- From the contact search results:
 - a) Tap **Keypad** at the bottom of the app.
 - b) Tap Q at the top right of the app.
 - c) Search for the contact's name or phone number.
 - d) Tap on the contact's profile picture in the search results.
- From the call history:
 - a) Tap **History** at the bottom of the app.
 - b) Tap on the contact's profile picture in the call history.

9 Favorites

Favorites allow you to easily access contacts you communicate with frequently. You can set a contact's phone number as a favorite for quick access to dial.

9.1 Marking a contact's phone number as a favorite

You can easily mark a contact's phone number as a favorite from the contact's profile page.

Step by Step

- 1) Go to the profile page of the contact you want to add to favorites in one of the following ways:
 - Tap **** Keypad at the bottom of the app, tap Q in the top-right of the screen, search for the contact's name or phone number, then tap on the contact's profile picture in the search results.
 - Tap () **History** at the bottom of the app, tap on the profile picture of the contact in the call history.
- **2)** Tap 1 to the right of contact's phone number.

The contact's phone number is added to your favorites list.

9.2 Reordering favorites

By default, the favorites list is updated automatically when you mark a contact's phone number as a favorite. The phone number you favorited last appears as the last item in the list.

You can easily rearrange your favorites in the order you want.

Step by Step

1) Tap \Leftrightarrow **Favorites** at the bottom of the app.

- **2)** Tap \mathcal{O} at the top right of the app.
- 3) Drag and drop your favorites in the order you want them to appear.
- 4) Tap \checkmark at the top right of the app to save the changes.

Your favorites list is updated and displays favorites in the order you arranged.

9.3 Removing a favorite

You can easily remove a favorite by following the steps below:

Step by Step

1) Tap \bigcirc **Favorites** at the bottom of the app.

- **2)** Tap \mathscr{O} at the top right of the app.
- **3)** Tap \ominus to the left of the favorite you want to remove.
- **4)** Tap \checkmark at the top right of the app to save the changes.

You can alternatively remove a favorite in one of the following ways:

- Tap \bigcirc **Favorites** at the bottom of the app, swipe left on the favorite you want to remove, then tap 1.
- Open the contact's profile page and tap the star icon.

The phone number is removed from your favorites list.

Next steps

If you want the add the phone number back to your favorites list, you need to mark it again as a favorite.

10 Settings

Use the Settings menu to configure the Unify Phone settings.

To open the **Settings** menu, tap \equiv in the top left of the app, then select **Settings** from the navigation drawer.

You can configure the following:

- Telephony settings:
 - Enable or disable Call forwarding.
 - Specify an Alternative number.
 - Activate your Voicemail.
 - Define the **Incoming call routing**.
 - Configure Busy settings.
- Theme:
 - Select a theme for the Unify Phone mobile app.
- Account
 - View the time of the last successful login.
 - Change your password
 - This is only available on Unify Phone for OpenScape.
- Contacts
 - Microsoft Exchange Online

Connect to your Microsoft Exchange Online account to access contacts.

Microsoft Exchange on-premises

Connect to your Microsoft Exchange on-premises account to access contacts.

- Google Contacts
- Connect to your Google account to access contacts.
- Ringtone
 - Select a ringtone for incoming calls.

10.1 Enabling call forwarding

You can redirect your phone calls to a person of your choice when you are out of office or unavailable by using **Call forwarding**.

- Tap ≡ in the top left of the app and select Settings from the navigation drawer.
- 2) Select the Telephony tab.
- 3) Switch the Call forwarding slider to ON (blue) to enable call forwarding.
- 4) Tap **Call forwarding number** and enter your colleague's phone number in the input field.
- 5) Tap OK.

Call forwarding is enabled and the **Forward calls to** field shows the forwarding destination.

NOTICE: When **Call Forwarding** is enabled , the **Incoming call routing** setting is not visible under **Settings** > **Telephony**.

10.2 Disabling call forwarding

Step by Step

- 1) Tap \equiv in the top left of the app and select **Settings** from the navigation drawer.
- 2) Select the Telephony tab.
- 3) Switch the Call forwarding slider to OFF (grey) to disable call forwarding.

NOTICE: When **Call Forwarding** is disabled, the **Incoming call routing** setting is visible under **Settings** > **Telephony**.

10.3 Setting an alternative number

You can set the phone number of an alternative device, e.g. mobile, that can be used for making and receiving phone calls through your work number. You also use the alternative number to control the routing of your calls between your devices.

Step by Step

- 1) Tap \equiv in the top left of the app and select **Settings** from the navigation drawer.
- 2) Select the Telephony tab.
- 3) Switch the Alternative number slider to ON (blue).
- **4)** Type the phone number of an alternative device in the input field or select one from the suggestions list.

The list displays the most recently set alternative numbers (up to 5) and is updated as you type in.

5) Tap OK.

The **Alternative number** field shows the phone number of the alternative device.

NOTICE: Successive changes of the alternative number in a very short period of time (i.e., in the order of a few seconds) can trigger the Denial-of-Service protection mechanism of your company's Session Border Controller, resulting in you being blocked from accessing telephony service for a configured period of time.

Settings Changing the ring time before a call is routed to alternative number

10.4 Changing the ring time before a call is routed to alternative number

When you have set your incoming calls to go through the default routing sequence and you have set an alternative number, you can further adjust how long your Unify Phone clients (web or mobile) and desk phone should ring before a phone call is routed to alternative number.

Step by Step

- 1) Tap \equiv in the top left of the app and select **Settings** from the navigation drawer.
- 2) Select the Telephony tab.
- 3) Locate the Incoming call routing section.
- 4) Tap the timer displayed below the **Default routing** option and choose the ring time that best suits your needs.

10.5 Activating your voicemail

You can specify whether or not your unanswered calls will go to voicemail.

NOTICE: Your telephony administrator has enabled voicemail on your company's communication system.

Step by Step

- 1) Tap \equiv in the top left of the app and select **Settings** from the navigation drawer.
- 2) Select the Telephony tab.
- 3) Switch the Voicemail slider to ON (blue).
- 4) Tap Active after to set the ringing duration of the call. The minimum ringing duration is 5 seconds and the maximum is 30 seconds.

10.6 Configuring incoming call routing

By default, incoming phone calls will ring on all of your Unify Phone clients and desk phone. On no answer they will be routed to your alternative device, if you have specified one.

You can change this default setting and have all incoming phone calls be routed directly to your desk phone or alternative device, if you know, for example, that you will be on this phone for a certain period of time.

- Tap ≡ in the top left of the app and select Settings from the navigation drawer.
- 2) Select the Telephony tab.

3) Tap Incoming call routing and choose one of the following options:

Default routing

Incoming calls will ring on all your Unify Phone clients and desk phone. On no answer, they will be routed to your alternative device, if you have specified one.

Desk Phone

Incoming calls will be routed directly to your desk phone.

Alternative number

Incoming calls will be routed directly to your alternative device.

Voicemail

Incoming calls will be routed directly to your voicemail.

NOTICE:

Outgoing calls are possible via all your Unify Phone clients or desk phone.

The option to send your incoming calls directly to your alternative device is only available if you have specified an alternative number.

The option to send your incoming calls directly to voicemail requires you to enable voicemail in settings and your telephony administrator to enable voicemail on your company's communication system.

10.7 Configuring busy settings

When you have set your incoming calls to go through the default routing sequence, you can further specify how new incoming calls will be treated while you are busy on a phone call. You can have these calls continue default routing, get a busy signal, go to your voicemail or alternative number, if you have specified one.

- 1) Tap \equiv in the top left of the app and select **Settings** from the navigation drawer.
- 2) Select the Telephony tab.

- 3) Tap Busy settings and choose one of the following options:
 - Default routing

New incoming calls will use default routing.

Busy signal

New incoming calls will get a busy signal.

Alternative number

New incoming calls will go to your alternative number.

Voicemail

New incoming calls will go to voicemail.

NOTICE:

The **Busy settings** section is visible when the **Default routing** is selected as the preferred option for **Incoming call routing**.

The option to send your new incoming calls directly to your alternative device is only available if you have specified an alternative number.

The option to send your new incoming calls directly to voicemail requires you to enable voicemail in settings and your telephony administrator to enable voicemail on your company's communication system.

10.8 Selecting a theme

Unify Phone mobile app currently supports three themes: system default, light and dark.

You can change the theme of your Unify Phone mobile app at any time.

Step by Step

1) Tap \equiv in the top left of the app and select **Settings** from the navigation drawer.

2) Tap Theme.

3) On the pop-up window, select the theme you want to use.

The theme will change automatically to the one that you have selected.

10.9 Connecting to your Microsoft Exchange account

You can connect to your company's Microsoft Exchange Online account to use your private and global Exchange contacts for phone calls.

Exchange contacts are shown with the Microsoft Exchange Online icon (I) at the top right corner of their avatar.

Prerequisites

A Microsoft Tenant administrator from your company must grant admin consent for the Unify Phone app on their tenant.

Step by Step

- 1) Tap \equiv in the top left of the app and select **Settings** from the navigation drawer.
- 2) Tap Contacts.
- 3) Tap Connect under the Microsoft Exchange Online area.

According to your connection status, the button in the Microsoft Exchange Online area displays:

- Connect, when you are not connected to Microsoft Exchange Online.
- Disconnect, when you are connected to Microsoft Exchange Online.
- 4) When prompted, sign in to your Microsoft Exchange Online account.
- 5) If this is the first time you are connecting to your Microsoft Exchange Online account, tap **Accept** to allow Unify Phone to access your contacts.

Next steps

You can disconnect from your Microsoft Exchange Online account at any time by tapping **Disconnect**.

If your favorites list includes phone numbers of Microsoft Exchange Online contacts, upon disconnecting, you will be prompted to choose whether to delete or keep these favorite phone numbers. If you choose to delete them, they will be deleted from your favorites list on all Unify Phone clients. If you choose to keep them, they will remain on Unify Phone. You can always delete favorites manually later.

10.10 Connecting to your Microsoft Exchange on-premises account

You can connect to your company's Microsoft Exchange on-premises account to use your private and global Exchange contacts for phone calls.

Exchange contacts are shown with the Microsoft Exchange on-premises icon (¹) at the top right corner of their avatar.

- 1) Tap \equiv in the top left of the app, then tap **Settings**.
- 2) Tap Contacts.
- Tap Connect under the Microsoft Exchange on-premises area. You are navigated to a new screen.

- 4) Enter your account's information:
 - Enter your Microsoft Exchange username in the form of username@domain in the Exchange username field.
 - · Enter your password in the Exchange password field.
 - Enter your service URL in the Exchange web service URL field.

The service URL must start with https://.

All fields are mandatory and cannot be omitted.

5) Tap Connect

According to your connection status, the button in the Microsoft Exchange onpremises area displays:

- Connect, when you are not connected to Microsoft Exchange on-premises.
- Disconnect, when you are connected to Microsoft Exchange on-premises.

Connecting to your Exchange account will automatically grant full mailbox access to Unify Phone.

Next steps

You can disconnect from your Microsoft Exchange on-premises account at any time by tapping **Disconnect**.

If your favorites list includes phone numbers of Microsoft Exchange onpremises contacts, upon disconnecting, you will be prompted to choose whether to delete or keep these favorite phone numbers. If you choose to delete them, they will be deleted from your favorites list on all Unify Phone clients. If you choose to keep them, they will remain on Unify Phone. You can always delete favorites manually later.

If you have previously connected to a Microsoft Exchange on-premises account, Unify Phone remembers the username and service URL you have used and automatically fills them in. Your Exchange password is not remembered and you must enter it again every time you connect to Microsoft Exchange on-premises.

10.11 Connecting to your Google account

You can connect to your Google account and use your Google contacts for phone calls.

Google contacts are shown with the Google icon (•) at the top right corner of their avatar.

Step by Step

- 1) Tap \equiv in the top left of the app, then tap **Settings**.
- 2) Tap Contacts.
- 3) Tap Connect under the Google Contacts area.
- 4) When prompted, sign in to your Google account.

According to your connection status, the button in the Google Contacts area displays:

Connect, when you are not connected to your Google account.

Disconnect, when you are connected to your Google account.

Next steps

You can disconnect from your Google account at any time by tapping **Disconnect**.

If your favorites list includes phone numbers of Google contacts, upon disconnecting, you will be prompted to choose whether to delete or keep these favorite phone numbers. If you choose to delete them, they will be deleted from your favorites list on all Unify Phone clients. If you choose to keep them, they will remain on Unify Phone. You can always delete favorites manually later.

10.12 Making yourself available for hunt/ ACD group calls

You can easily make yourself available or unavailable to receive hunt/ ACD group calls. You simply need to set your agent status to the appropriate value.

As an **OpenScape Voice subscriber**, you can be a member of multiple hunt groups at a time. You can see the list of all hunt groups that you are a member

of under the **Agent status** section, by tapping \equiv in the top left of the app. You can make yourself available or unavailable for hunt group calls to all the hunt groups at once or to an individual hunt group.

As an **OpenScape 4000 subscriber**, you can be a member of either one ACD group or a member of one or more classic hunt groups. As a Unify Phone user, you cannot be part of both an ACD group and one or more classic hunt groups at the same time. You can see your agent status under the **Agent status**,

by tapping \equiv in the top left of the app. You can make yourself available or unavailable for ACD group calls or for calls to all hunt groups you are a member of at once.

10.12.1 Making yourself available for hunt group calls (OpenScape Voice)

Prerequisites:

• You are a member of at least one hunt group.

You can see your agent status under the **Agent status** section, by tapping \equiv .

The agent statuses are described in the following table:

Agent status	Description
🕄 Unavailable	You are unavailable for calls to any hunt group.
🖓 Partially unavailable	You are unavailable for calls to some but not all hunt groups.
Available	You are available for calls to any hunt group.

Your agent status is available by default. If you do not answer a hunt group call that is ringing you during a longest idle, linear or circular hunting, your status for this group will be set to unavailable. As a result, your agent status will be automatically set (if not already) to Partially unavailable or Unavailable, depending on whether you are still available for calls to other hunt groups you are a member of. You need to set your agent status back to available, when you are ready again for hunt group calls.

Procedure

- 1) To make yourself available for calls to an individual hunt group:
 - a) Tap \equiv in the top left of the app.
 - b) Tap Agent Status.
 - c) Locate the hunt group of your interest and switch the nearby slider to ON (green).

You will be able to receive calls to the phone number of this specific hunt group.

Your agent status is updated (if not already) to **Partially unavailable** (yellow) or **Available** (green), depending on whether you are still unavailable for calls to at least one hunt group.

- 2) To make yourself available for calls to any hunt group at once:
 - **a)** Tap \equiv in the top left of the app.
 - b) Tap Agent Status.
 - c) Locate the general agent status slider, under the Agent Status section.
 - d) Switch the general agent status slider to ON (green).

You will be able to receive calls on the phone number of any hunt group you are a member of.

Your agent status is updated to **Available** (green).

- 3) To make yourself unavailable for calls to an individual hunt group:
 - a) Tap \equiv in the top left of the app.
 - b) Tap Agent Status.
 - c) Locate the hunt group of interest, and switch the slider next to it to OFF (gray).

Phone calls to the phone number of this specific hunt group will not come in on your device.

You agent status is updated (if not already) to **Partially unavailable** (yellow) or **Unavailable** (gray), depending on whether you are still available for calls to other hunt groups you are a member of.

- 4) To make yourself unavailable for calls to any hunt group at once:
 - **a)** Tap \equiv in the top left of the app.
 - b) Tap Agent Status.
 - c) Locate the general agent status slider, under the Agent Status section.
 - d) Switch the general agent status slider to OFF (gray).

Phone calls to the phone number of any hunt group you are a member of will not come in on your device.

Your agent status is updated to Unavailable.

Your agent status does not affect the delivery of normal phone calls to your own number. So even when you are unavailable for hunt group calls, you can still receive direct calls to your work number.

10.12.2 Making yourself available for ACD group calls (OpenScape 4000)

Prerequisites

- You are configured as an agent.
- You are a member of an ACD group.
- You are logged on as an agent.

As a member of an ACD group, you can easily make yourself available or unavailable for ACD group calls. You simply need to set your agent status to the appropriate value.

The agent statuses are described in the following table:

Agent status	Description
Unavailable	You are unavailable for calls to the ACD group.
	The agent slider is switched to OFF (grey).
Available	You are available for calls to the ACD group.
	The agent slider is switched to ON (green).
Working after call	You are unavailable for calls to the ACD group.
	The agent slider is switched to OFF (grey).

Your agent status is unavailable by default if you log on manually, from your desk phone.

Your agent status is set to available by default if auto-log on is configured.

When the service out feature is configured, if you do not answer an ACD group call until a predefined timer expires, your status will be set to unavailable. You need to set your agent status back to available, when you are ready to receive ACD group calls again.

Step by Step

- 1) If auto-log on is not configured, do the following to log on as an agent:
 - a) On your desk phone, press the ACD log key and enter the Agent ID.

NOTICE: This option is not available for SIP devices.

- b) On your desk phone, enter the **ACD log on code**, followed by the **Agent ID**.
- 2) To make yourself available for ACD group calls, you need to:
 - a) Tap \equiv in the top left of the app.
 - b) Switch the slider to ON (green) to make yourself available to receive ACD group calls.

Phone calls to the phone number of the ACD group you are a member of will come in on your device.

Your agent status is set to Available.

- 3) To make yourself unavailable for ACD group calls, you need to:
 - a) Tap \equiv in the top left of the app.
 - b) Switch the slider to OFF (gray) to make yourself unavailable to receive ACD group calls.

Phone calls to the phone number of the ACD group you are a member of will not come in on your device.

- 4) If the working after call feature is configured for your agent, your status will automatically switch to unavailable, at the end of an ACD call. When the working after call timer expires, your status will be switched back to available.
- 5) To log off as an agent, do the following:
 - a) On your desk phone, press the ACD log key then enter the ACD log off code.

Your agent status does not affect the delivery of normal phone calls to your own number. So, even when you are unavailable for ACD group calls, you can still receive direct calls to your work number.

10.12.3 Making yourself available for classic group calls (OpenScape 4000)

Prerequisites

- You are configured as a hunt group member.
- You are a member of one or more classic hunt groups.
- You are logged on as a hunt group member.
- Your OpenScape 4000 communication system is running at least on version 11.

As a member of a classic hunt group, you can easily make yourself available or unavailable for hunt group calls. You simply need to set your agent status to the appropriate value.

The agent statuses are described in the following table:

Agent status	Description
Unavailable	You are unavailable for calls to any classic hunt group.
	The agent slider is switched to OFF (gray).
Available	You are available for calls to any hunt group.
	The agent slider is switched to ON (green).

Your agent status is unavailable by default if you log on manually, from your desk phone.

Your agent status is set to available by default if auto-log on is configured.

When the service out feature is configured, if you do not answer until a predefined timer expires, your status will be set to unavailable. You need to set

your agent status back to available, when you are ready to receive hunt group calls again.

If you are a member of multiple classic hunt groups at a time, your agent status shows your availability for all groups you are a member of.

Changes in your availability are also possible via alternative ways (e.g. AMO commands, dedicated keys on the desk phone, dialing an access code). If such actions are executed, then you must sign out and sign in again to Unify Phone to retrieve the changes in the classic hunt group information from the OpenScape 4000 side.

For example, if you are a subscriber of OpenScape 4000 and you have been added as a member to a classic hunt group or you have logged into the classic hunt group after signing in to Unify Phone, you must sign out and sign in again to Unify Phone for the system to retrieve the correct hunt group information.

Similarly, if you make yourself unavailable for classic hunt group calls via an alternative way (e.g. AMO commands, dedicated keys on desk phone, dialing an access code), then the changes in your availability status will not be propagated to Unify Phone. You must authenticate again to Unify Phone to retrieve the changes in the classic hunt group information from the OpenScape 4000 side.

Step by Step

- 1) To make yourself available for classic hunt group calls, you need to:
 - a) Tap \equiv in the top left of the app.
 - b) Switch the slider to ON (green) to make yourself available to receive classic hunt group calls.

Phone calls to the phone number of the classic hunt group you are a member of will come in on your device.

Your agent status is updated (if not already) to Available.

- 2) To make yourself unavailable for classic hunt group calls, you need to:
 - ^{a)} Tap \equiv in the top left of the app.
 - b) Switch the slider to OFF (grey) to make yourself unavailable to receive classic hunt group calls.

Phone calls to the phone number of the classic hunt group you are a member of will not come in on your device.

Your agent status does not affect the delivery of normal phone calls to your own number. So, even when you are unavailable for classic hunt group calls, you can still receive direct calls to your work number

10.13 Changing your password

You can change your password any time you are signed in to Unify Phone for OpenScape.

Prerequisites

You are signed in with your Unify Phone credentials.

NOTICE: If you are signed in through SSO, you cannot change your password by following the steps outlined below; you need to change your password outside of the Unify Phone app, in the third-party service that provides the SSO.

Step by Step

- 1) Tap \equiv in the top left of the app and select **Settings** from the navigation drawer.
- 2) Select the Account tab.
- 3) Tap Change Password.
- 4) Enter your email address in the Email field and tap Next.
- 5) Enter your old password in the **Password** field and tap **Sign In**.
- 6) Enter your new password in the **New password** field, then enter it again in the **Confirm new password** field.

The password must conform to the password requirements displayed.

As you type in, a visual strength indicator shows how secure your password is.

For security reasons, you cannot reuse a few passwords that you have previously set on your account. If the new password matches a recent password from the password history cache, an error message is displayed prompting you to choose a different password.

7) Tap Submit.

Your password is changed.

NOTICE: Your password is set to expire automatically every 90 days. You will receive an email reminder 7 days prior to your password expiration date. We recommend changing your password before it expires to avoid losing access to your account. Remember to check your junk or spam folder if you can't find the email in your inbox.

10.14 Changing the Unify Phone ringtone for incoming calls

You can change the ringtone for incoming calls to easily recognize calls that come in on your Unify Phone app.

Before changing the ringtone, the **Default** one is used.

Step by Step

 Tap ≡ in the top left of the app and select Settings from the navigation drawer.

2) Tap Ringtone.

The list of available rightones is displayed.

3) Tap any ringtone to play it or select it as the ringtone for incoming calls.

When a ringtone is selected, the entry turns blue and the \checkmark icon is displayed on the right.

The ringtone for incoming calls on your Unify Phone app is updated.

10.15 Viewing your account's activity

You can view the time of the last successful authentication to Unify Phone and track your account's activity.

Step by Step

- 1) Tap \equiv in the top left of the app, then tap **Settings**.
- 2) Tap Account.

The date and time of the last successful sign-in are displayed.

11 Service and support

User documentation

You can access user documentation from the Unify Phone mobile app. For more information, please refer to section Accessing user documentation on page 54.

Service requests

If you have an issue or want to give us feedback, please refer to section Reporting an issue on page 54.

11.1 Accessing user documentation

You can access the Unify Phone for Android user guide from within the app at any time.

Documentation is available in PDF and HTML formats.

Step by Step

- 1) Tap \equiv in the top left of the app and select **Help** from the navigation drawer.
- 2) Tap Open PDF or Open HTML according to your preference.

11.2 Reporting an issue

If you are experiencing an issue with Unify Phone, you can report it from within the app.

Step by Step

- Tap ≡ in the top left of the app and select **Report issue** from the navigation drawer.
- 2) From the pop-up menu, select Share logs.
- **3)** Select the email app.
 - The email app opens with a pre-populated message and with the log files as an attachment.
- **4)** Provide a short description of the issue in the subject line and a detailed description of the issue in the email body.

When describing the issue, please indicate:

- a) The approximate time the problem happened
- b) How often the issue occurs
- c) What you were doing when the issue occurred
- d) Attach any screenshots that might help troubleshoot the issue
- 5) Send the email.

11.3 Viewing the terms and conditions

You can view terms and conditions any time you want from within the Unify Phone app.

Procedure

• Tap ≡ in the top left of the app and select **About** from the navigation drawer.

11.4 Performing a required update of the Unify Phone app

Unify Phone checks for updates when you sign in and when the app is brought to the foreground.

If a new version is found and the security and functionality of the Unify Phone app is at risk, you will receive a notification informing you that an app update is required. You cannot continue using the app until the new version is installed. Not updating the app when required will result in incoming calls being missed and an in-app notification that you are missing calls on Unify Phone because your app is outdated.

To update your Unify Phone app to the latest version:

Step by Step

- 1) Tap Update in the in-app notification.
 - You are directed to the app store.
- 2) Select to update Unify Phone.

Depending on the size of the update and the speed of your internet connection, the process can take some time to complete.

11.5 Granting additional app permissions when Unify Phone runs on a Xiaomi device

For Unify Phone to work properly on a Xiaomi device, you need to manually grant the app with a set of UI permissions.

- 1) To allow Unify Phone to use the background autostart service:
 - a) On your device Settings, navigate to Apps > Permissions > Autostart.b) Switch the slider next to Unify Phone to ON.
- 2) To allow Unify Phone to show notifications on phone's lock screen:
 - a) On your device **Settings**, navigate to **Apps > Permissions > Other permissions**.
 - b) Tap **Permissions > Show on Lock screen**.
 - c) Enable the checkbox next to Unify Phone.

These steps may vary depending on the MIUI version.

12 Appendix

This section contains additional reference information.

12.1 Switching your Chromebook to Beta channel

You can switch your Chromebook to Beta channel by following the steps below:

Step by Step

- 1) Sign in to your Chromebook with the owner account.
- 2) At the bottom right, click the time and then select Settings > About ChromeOS > Additional details.
- 3) In the Channel area, click Change channel, then select the Beta channel.
- 4) Go back to the About ChromeOS area and click Check for updates.

Your Chromebook downloads and installs the latest Chrome OS beta build.

- 5) Restart your Chromebook to complete the update.
- 6) Go to Settings > Apps > Manage Android preferences > System > About Device and check that you are using Android version 11.
- 7) If your Chromebook is based on Hatch and you have not received the Android 11 update in the latest Beta build, remove the existing Android setup and install it again:
 - a) Navigate to Settings > Apps > Remove Play Store and select Remove.
 - b) Turn on Play Store from the Apps page and install it again. Installing Play Store again will remove all your Android apps.

mitel.com

🕅 Miteľ

© 2025 Mitel Networks Corporation. All Rights Reserved. Mitel and the Mitel logo are trademark(s) of Mitel Networks Corporation. Unify and associated marks are trademarks of Unify Software and Solutions GmbH & Co. KG. All other trademarks herein are the property of their respective owners.